

## Monet™ Architectural Specification Grade Scene-Capable Controls 120V & 277V AC 60Hz

Low-profile Architectural Decora Digital Preset Slide Dimmers with LED locator light. All Monet dimmers provide single-pole (1 location) and 3-way (multi-location) control with Switching Remote, plus Scene Capabilities when used with Monet Scene Controller units.

### *Incandescent 120V AC*

DESCRIPTION	CAT. NO.	RATING	COLOR*
Monet Dimmer (narrow fin)	MNI06-1L	600W	I, W, G, E, A
Monet Dimmer (narrow fin)	MNI10-1L	1000W	I, W, G, E, A
Monet Dimmer (wide fin)	MNI15-1L	1500W	I, W, G, E, A

### *Low-Voltage 120V AC*

DESCRIPTION	CAT. NO.	RATING	COLOR*
Monet Dimmer (narrow fin) Electronic	MNE04-1L	400VA (300W)	I, W, G, E, A
Monet Dimmer (narrow fin) Magnetic	MNM06-1L	600VA (450W)	I, W, G, E, A
Monet Dimmer (narrow fin) Magnetic	MNM10-1L	1000VA (750W)	I, W, G, E, A
Monet Dimmer (wide fin) Magnetic	MNM15-1L	1500VA (1125W)	I, W, G, E, A

### *MarkX™ Fluorescent Ballast*

For Advance Mark X™ fluorescent dimming ballasts.

DESCRIPTION	CAT. NO.	RATING	COLOR*
Monet Mark X Fluorescent Dimmer (narrow fin)	MNX10-1L	1000VA (750W) 120V AC	I, W, G, E, A
Monet Mark X Fluorescent Dimmer (wide fin)	MNX15-1L	1500VA (1125W) 120V AC	I, W, G, E, A
Monet Mark X 277V Fluorescent Dimmer (narrow fin)	MNX20-7L	2000VA (1500W) 277V AC	I, W, G, E, A
Monet Mark X 277V Fluorescent Dimmer (wide fin)	MNX30-7L	3000VA (2250W) 277V AC	I, W, G, E, A

### *Fan Speed Controls 120V AC*

DESCRIPTION	CAT. NO.	RATING	COLOR*
Monet Fan Speed Control (narrow fin)	MNF07-1L	7.5A 120V AC	I, W, G, E, A
Monet Fan Speed Control (wide fin)	MNF10-1L	10A 120V AC	I, W, G, E, A

### *Monet™ Products*

DESCRIPTION	CAT. NO.	RATING	COLOR*
Monet Scene-Capable Digital Multi-Location Switch—Non-Dimming, Lighted (narrow fin)	MNS10-1L	1000VA (750W) 120 VAC Magnetic Low-Voltage, Magnetic and Electronic Fluorescent	I, W, G, E, A
Monet Remote Non-Dimming Switching Unit for 3-Way Applications (Unlighted)	MN00R-DOW	No load rating, use with 120V & 277V Monet dimmers only	White, for other colors use Color Change Kits
Color Change Kits for MN00R-10W Monet 3-Way Switching Unit	MNK0R-00	—	I, W, G, E, A
Monet Adapter Plate: Allows any Decora strap-mount device to be ganged with either small or large-size Monet controls. In multi-gang installations, must use on ends	MNOLA-000 (large) MNOSA-000 (small)	—	Metal Heat Sink

**Note:** Mark X™ is a trademark of the Advance Transformer Company.

**Note:** Sharing a neutral wire may cause flickering. Connect all dimmers to the same phase or run a separate neutral to each device. Consult Leviton Techline if problems persist.

Digital Lighting and Fan Speed Controls are polarity sensitive devices. Always follow the wiring instructions included with each device. They can be used in conventional 3-way and 4-way wiring circuits only when the Control is properly connected to the load as indicated by the device's wiring instructions.

**CAUTION ON RETROFITS:** When retrofitting Mark X dimming ballasts into fixtures that originally had Instant Start ballasts, the sockets MUST be replaced with Rapid Start sockets to allow proper dimmer operation and prevent damage to the dimming ballast. Refer to the instructions provided with the ballast and the Leviton Mark X dimmer.



MNI06-1LW



MNI15-1LW

**NOTE:** Multi-gang wallplates are available for combining narrow and wide dimmers, with or without fins removed. Refer to page O15.

**Monet Architectural Fin Width**  
Narrow: 2.75" (69.9 mm)  
Wide: 4.25" (108.0 mm)

