

PowerVerter Ultra-Compact Inverter

Portable Power for All Applications



Model #: PV375

- ▶ 12V DC input; 120V AC output; 2 outlets
- ▶ 375 watts continuous output
- ▶ 600 watts peak output
- ▶ Convenient cigarette lighter plug

DESCRIPTION

Harness your vehicle's battery to efficiently power office equipment on the road. Continuously supplies up to 375 watts of 120V AC power to 2 AC outlets from any 12V battery or automotive DC source. Convenient cigarette lighter DC input jack with 3-ft. cable provides 1-step installation. Portable and compact, the inverter's design is among the most rugged available thanks to its lightweight metal casing.

KEY BUYING POINTS

- Allows users to run AC appliances from any 12V cigarette lighter socket
- Converts 12V DC battery power to 120V AC power
- 375 watts continuous output power; 600 watts peak output power
- 2 outlets
- 3-ft. cord with cigarette lighter plug
- Ultra compact, lightweight design with all-metal housing
- Low battery alarm with auto-shutoff preserves vehicle battery
- Overload alarm with auto-shutoff prevents wattage overload
- Replaceable fuse protects inverter from overload
- Lighted power switch
- 1 year manufacturer's product warranty



TYPICAL APPLICATIONS

- Ideal for laptop computers, portable electronics, battery chargers for cell phones, pagers, notepads, game systems, personal printers and battery rechargers for small battery-operated power tools, portable TV-VCR-stereo systems, camcorders, lighting and other low-power applications under 375 watts.

PACKAGE INCLUDES

- PV375 Inverter
- Warranty information
- Instruction manual

COMPLETE SPECIFICATIONS

SYSTEM OVERVIEW	
System overview:	Compact 12 volt DC to 120 volt AC power inverter. 375 watts continuous / 600 watts peak. Cigarette lighter input jack, 2 AC outlets.
Voltage compatibility:	Compatible with 12V DC automotive systems
Frequency compatibility:	60 Hz