




































# Floor Boxes Technical Data

## Hubbell Selector Chart, Receptacles, Covers

Cover Style	Terazzo	2 1/8"	2 1/2"	2 3/8"	Duplex Flap	Duplex Plug	Style Line	2 1/8"	2 1/2"	2 3/8"
Round	 <b>S3325</b>	 <b>S3525</b>	 <b>S2925</b> <b>SA2925</b> <b>SF2925</b>		 <b>S3925</b> <b>SA3925</b> <b>SF3925</b>	 <b>S3725</b> <b>SA3725</b>		 <b>S88</b>	 <b>S2955</b>	 <b>S2930</b>
Rectangular		 <b>S3425</b>		 <b>S2825</b>	 <b>S3825</b> <b>SA3825</b>	 <b>S3625</b> <b>SA3625</b>	 <b>S3826*</b> <b>SA3826</b>			

Rating	Configuration	NEMA										
2P, 3W 15A, 125V		5-15R	HBL5251 HBL5261	HBL5251 HBL5261	HBL5251 HBL5261	HBL5251 HBL5261	CR5262 CR5252IG HBL5242 HBL5252 HBL5262 IG5262	CR5262 CR5252IG HBL5242 HBL5252 HBL5262 IG5262	HBL2152 IG2152 GFR5252A HBL5262SA	HBL5258 HBL5284	HBL5258 HBL5284	HBL5258 HBL5284
2P,3W 15A, 125V		L5-15R	HBL4710	HBL4710	HBL4710	HBL4710	HBL4700 IG4700A HBL4792 HBL4794 HBL4795	HBL4700 IG4700A HBL4792 HBL4794 HBL4795		HBL4713 HBL4713	HBL4713 HBL4713	HBL4713 HBL4713
2P, 3W 15A, 250V		6-15R	HBL5651 HBL5661	HBL5651 HBL5661	HBL5651 HBL5661	HBL5651 HBL5661	HBL5652 HBL5662	HBL5652 HBL5662		HBL5658 HBL5658	HBL5658 HBL5658	HBL5658 HBL5658
2P, 3W 15A, 250V		L6-15R	HBL4560	HBL4560	HBL4560	HBL4560	HBL4550	HBL4550		HBL4563 HBL4563	HBL4563 HBL4563	
2P, 3W 15A, 277V		7-15R					HBL5302	HBL5302				
2P, 3W 15A, 277V		L7-15R	HBL4760	HBL4760	HBL4760	HBL4760	HBL4750	HBL4750		HBL4763 HBL4763	HBL4763 HBL4763	
2P, 3W 20A, 125V		5-20R	HBL5351 HBL5361	HBL5351 HBL5361	HBL5351 HBL5361	HBL5351 HBL5361	CR5362 CR5352IG HBL5342 HBL5352 HBL5362 IG5362	CR5362 CR5352IG HBL5342 HBL5352 HBL5362 IG5362	HBL2162 IG2162 GFR5352A HBL5362SA	HBL5358 HBL5358	HBL5357 HBL5357	HBL5358 HBL5358
2P, 3W 20A, 125V		5-20R					HBL5392	HBL5392				
2P, 3W 20A, 125V		L5-20R	HBL2310	HBL2310	HBL2310							
2P, 3W 20A, 250V		6-20R	HBL5461	HBL5461	HBL5461	HBL5461	HBL5462	HBL5462				
2P, 3W 20A, 250V		L6-20R	HBL2320	HBL2320	HBL2320							
2P, 3W 30A, 125V		L5-30R	HBL2610	HBL2610	HBL2610							
2P, 3W 30A, 250V		L6-30R	HBL2620	HBL2620	HBL2620							
3P, 4W, 20A 125/250V		14-20R L14-20R	HBL8410 HBL2410	HBL8410 HBL2410		HBL8410 HBL2410						
3P, 4W, 20A 30 250V		15-20R L15-20R	HBL8420 HBL2420	HBL8420 HBL2420		HBL8420 HBL2420						
3P, 4W, 30A 125/250V		L14-30R	HBL2710	HBL2710								
3P, 4W, 30A 3Ø 250V		L15-30R	HBL2720	HBL2720								
3P, 4W, 30A 3Ø 600V		L17-30R	HBL2740	HBL2740								
4P, 5W, 20A 3Ø Y 120/208V		L21-20R	HBL2510	HBL2510	HBL2510	HBL2510						
4P, 5W, 20A 3Ø Y 347/600V		L23-20R	HBL2530	HBL2530	HBL2530	HBL2530						
4P, 5W, 30A 3Ø Y 120/208V		L21-30R	HBL2810	HBL2810								
4P, 5W, 30A 3Ø Y 347/600V		L23-30R	HBL2830	HBL2830								

