

## Floor and Wall Boxes Accessories

Experiencing a problem? Let Hubbell accessories help solve it. Hubbell stacking (adjustable) collars are the answer if the box is set too low. Need a replacement? Choose from a full line of replacement covers and fittings. Hubbell accessories also help you with the protection you need for plugs and receptacles.

### Problem solvers & replacement components Stacking (adjustable) collars & frames.

Designed to be used if floor is set too low beneath the floor surface or the adjustable collar and/or adapter on the box is damaged.

If the box number is . . .	Use Collar Number	Extension Value
<b>B2429, B2427, B2436 or B2437</b>	<b>*C2400</b>	.81" (20.5)
<b>B2503, B2506</b>	<b>*C2504</b>	1.06" (26.9)
<b>B2529, B2536, B2527 or B2537</b>	<b>*C2500</b>	1.06" (26.9)
<b>B4233</b>	<b>*C4200</b>	1.03" (26.2)
<b>B4333</b>	<b>*C4300</b>	1.03" (26.2)

*Notes: \* Only available as sets (collars and adapters). In cases where the adapter on the floor box is not damaged, and stacking only is required, discard the adapter and use only the collar. The adjustable collars listed above can be stacked as required to reach the floor surface. Longer screws will be required if more than one collar is stacked (screws not provided). These screws are commercially available. Flat head #12-24UNC machine screw x (approx. length). Minor Upward Adjustments: Round or Rectangular cover frames (trim rings) may be stacked if the floor box is only slightly recessed below the floor surface.*

### Replacement Components for Floor Box Covers & Fittings

Box Type	Dimension	Use Flange Number	Extension Value
Round	4.19" (106.4) diameter	<b>S5016 or SA5016</b>	.31" (7.9)
Rectangular	3.19" (81.0) x 4.38" (111.2)	<b>S5017A or SA5017A</b>	.31" (7.9)

### Crown Plugs

Description	Used in the following covers	Catalog Numbers	
		Brass	Aluminum
3/4" thread size.	S2525, SA2525, S881, S2555, S2530, S2425, SA2425, SF2525	<b>S5012</b>	<b>SA5012</b>
1" thread size.	S2725, SA2725, S2755, S2730, S2625, SA2625, SF2725	<b>S5013</b>	<b>SA5013</b>

### Flush Cap Rings

Description	Used in the following covers	Catalog Numbers	
		Brass	Aluminum
2 1/8" threaded plug with 3/4" thread size opening.	S2525, SA2525, S881, S2555, S2530, S2425, SA2425, SF2525	<b>S5010</b>	<b>SA5010</b>
2 1/8" threaded plug with 1" thread size opening.	S2725, SA2725, S2755, S2730, S2625, SA2625, SF2725	<b>S5025</b>	<b>SA5025</b>

### Flush Plugs

Description	Used in the following covers	Catalog Numbers	
		Brass	Aluminum
3/4" I.P.S. thread size.	F1339, F1340	<b>S5002</b>	—
1" I.P.S. thread size.	F1539	<b>S5003</b>	—
1 1/2" fine thread size.	S3725, SA3725, S3625, SA3625	<b>S5007</b>	<b>SA5007</b>
2 1/8" fine thread size.	S2925, SA2925, S88, S2930, S2955, SF2925, S2825	<b>S5020</b>	<b>SA5020</b>
2 3/8" fine thread size.	S3525, S3425	<b>S5030</b>	—

### Replacement Adjustable Collar




### Cover Frame




### Adjustable Collar



### Adapter



### Box



### Replacement Cover Frames



**S5017A**

**S5016**

### Crown Plugs



**S5013**

**S5012**

### Flush Cap Rings



**S5010**

### Flush Plugs



**S5007**