



Compatible with:







SC911-15A Emergency Amplifier

The ideal 6-wire amplifier for Controller, Dispatch and 911 operations. Compatible with all dual plug prong 6-wire consoles.

The complete Sennheiser 911 System has ActiveGard in every Sennheiser CC and SH Series headset for user protection and safety.

Features / Benefits

- Connects to any Sennheiser CC and SH Series headset with the unique easy-disconnect
- Has momentary (non-locking) push-to-talk switch
- Connecter is 6-wire dual plug prong PJ-7 (equivalent to WE-425) with 15 ft. extra heavy-duty coil cord
- Receiver volume control and transmit output control
- Includes heavy-duty belt clip and lanyard (neck strap) cord
- ActiveGard is a technically advanced compression circuit that reacts 35 to 50 times faster than any other headset manufacturers compression circuit. The Sennheiser 911 system has a maximum receiver output of 103 dB SPL and is OSHA compliant

Technical Data

Receiver:

Frequency Response Input Impedance Maximum Output **Receive Volume Control Gain** 300-3300 Hz 600 Ohms (Typical) 103 dB SPL @ 1 kHz, 1 Vrms +20 dB

Transmit:

Frequency Response Output Impedance **Output Gain** Polarity Voltage Supplied by Console 100-4500 Hz 50 Ohms

Cables:

Connecting Cable Headset Interface +15 dB Non-polar 3 Vdc @ .26 mA

15 ft. coil cord with PJ-7 connector Easy-disconnect

Compliance:

CE Certified FCC part 15 Subpart B Certified OSHA part 1910 Subpart S Compliant

Sennheiser Electronic Corporation, One Enterprise Dr., Old Lyme, CT 06371 Tel: (860)-434-9190 Fax: (860) 434-1759 Web: www.sennheiserusa.com Latin America, Tel: 52 55-5639-0956 Fax: 52 55-5639-0956