

CHANNEL VISION's Telephone Entry System creates a communication link between your front door and every telephone in the house. The TE110 sends a distinctive ring to every telephone when the doorbell is pressed. Simply pick up any telephone handset to begin speaking to the visitor or by pressing “#” or “\*” at any time. The TE110 also includes an option to operate a door strike relay when used with the TE110DS (sold separately). Combine this unit with a CHANNEL VISION RF modulator and Front Door Intercom Camera Unit for a complete and easy to use residential audio/video access control package.



TE110BK

Refer to wiring diagrams on page 7



DP-9002



DP-RBox-II

## TE110

### Telephone Entry Controller

- Uses existing phone wiring
- Doorbell button sends a distinctive ring to phones to alert you that a visitor has arrived
- Seamless call waiting
- 3 different distinctive ring patterns
- Surface mount components for longer life
- Enclosure: C-0111 (12-3/4" x 7-1/2" mini security panel) includes lock and key
- Power Supply: 12VACDC, 500mA included
- Wiring: 2-conductor twisted pair between main board and companion board
- Also available as a snap in component for the structured wiring panels (refer to page 18)
- 2-Year Warranty

## TE110BK

### Telephone Entry Kit

- Includes a TE110 and an IU-0282 black intercom unit

## TE110WT

### Telephone Entry Kit

- Includes a TE110 and an IU-0212 white intercom unit (not shown)

## TE110DS

### Door Strike Relay

- For use with the TE110 system
- Compact size allows for versatile installation
- Single gang box stainless cover for easy installation and access
- Door strike not included
- Screw terminal wire connection

## DP-RBox-II

### Metal Flush Mount Rough-In Box

- For use with DP-series (sold separately)
- Dimensions: 6-1/8"(H) x 4"(W) x 3-1/4"(D)

## DP-9001 (White)

## DP-9002 (Black)

### Metal Surface Mount Box

- For use with DP-series
- DP-9001 is included with the white door plate
- DP-9002 is included with all other finishes.
- Dimensions: 6-7/16"(H) x 4-3/8"(W) x 1-3/4"(D)