

# Economy Surge Suppressor

## Rackmount surge protection



### Model #: DRS-1215

- ▶ 14 outlets / 15-ft. cord
- ▶ 1050 joule rating
- ▶ Adjustable rackmount hardware



## DESCRIPTION

Tripp Lite's DRS-1215 offers surge and noise suppression in a versatile all-metal multi-mount cabinet. Detachable mounting flanges are configurable for rackmount, wallmount and under-counter installation. Uses only 1 rack space (1U) when installed in any 19 inch EIA standard rack. Includes 14 outlets (6 front / 8 rear), 15 ft AC power cord and guarded power switch to reduce the risk of accidental shutoff. Diagnostic LED indicates surge protection status. Lifetime warranty.

PLUG / OUTLETS: Input: NEMA 5-15P / Output: 14 NEMA5-15R (6 front & 8 rear)

ELECTRICAL: 120V AC, 50/60Hz, 15A (Requires NEMA 5-15R wall receptacle)

SUPPRESSION: AC: 140V RMS Clamping / 1050 joules

FORMAT: Supports 19 in. rackmount (uses 1 rack space / 1U), wallmount, under-counter and more

## KEY BUYING POINTS

- Versatile all-metal cabinet with detachable mounting flanges allows rackmount, wallmount, undercounter and other creative mounting options
- Uses one rack space (1U) in standard 19 inch rack ("zero U" mounting possible in many racks)
- 1050 joules AC surge suppression with EMI/RFI filtering
- 14 NEMA 5-15R output receptacles (6 front / 8 rear)
- 15 foot AC cord with NEMA 5-15P straight-in plug connection
- Diagnostic LED confirms suppressor operation
- Lighted power switch confirms power on/off status
- Snap-in switch guard prevents accidental turn off
- 15 amp capacity with circuit breaker
- 120V AC, 50/60Hz electrical compatibility
- Lifetime product warranty

## TYPICAL APPLICATIONS

- Ideal for protection of sensitive electronic equipment in 19 inch rackmount, wallmount and under-counter applications, such as internetworking equipment, PC systems, telecommunications, audio/video, security, sound reinforcement and more.

## PACKAGE INCLUDES

- DRS-1215 Surge Suppressor
- Warranty information
- Instruction manual

## COMPLETE SPECIFICATIONS