




# The only answer to Modulating on Digital Cable...Guaranteed!

**AFFINITY™**

## P-0321 **PRO** Digital Cable Combiner

The P-0321 allows you to integrate modulated signals into a digital cable system without using an RF filter. This allows modulated channels to be integrated with a full digital cable feed without requiring any digital TV channels to be filtered out.

- Eliminates Cable Interference Without Filters
- Easy Source Switching
- Today's only Modulation Solution
- Future-Proof
- Eliminates Call Backs
- Remote Control, IR-Receiver, IR Coax Adapter and Power Supply Included
- Patent Pending Technology



**Specifications:** (typical at 25 degrees C)

**Forward Gain:**

CATV in to out 54-1000MHz + 4dB  
 MOD in to out 54-1000MHz -13dB

**Reverse Channel:**

Out to CATV in 5-42MHz <-7dB

**Isolation:**

CATV in to TV output 54-1000MHz >50dB (60dB typical)  
 MOD in to TV output 54-1000MHz >50dB (60dB typical)

**IR Over Coax:**

Compatible with Channel Vision IR-4100 and IR-4101 only

**Power Supply:**

12VDC, 250mA unregulated

Specifications subject to change without notice.

**Accessories included:**

Remote



IR-4100 Coax Adapter



IR-2400 IR-Receiver



Power Supply



**IR-Receiver Spec:**

IR Frq. range supported: 30kHz-60kHz

**IR Pickup Range:**

40 ft. @ 38kHz, 25ft @ 56kHz

**IR Receiver Head Dimensions:**

0.6" x 0.35" x 0.25"

Specifications subject to change without notice.

**CHANNEL VISION™**

[www.channelvision.com](http://www.channelvision.com)

**800.840.0288**

234 Fischer Ave., Costa Mesa, CA 92626 • USA

A-BUS® is a registered trademark of LeisureTech Electronics Pty Ltd. Australia. Channel Vision Technology, Channel Vision Central and ARIA are trademarks of Channel Vision Technology, Channel Vision™ Technology 2006©



Channel Vision Central Structured Wiring



Channel Vision Pro IR & Audio Equipment



ARIA & Multi-Room Audio



Channel Vision Technology Modulators, Cameras, Intercoms

P-0321 cut sht.qxp