





## HUBBELL Advantage

- Made with Premium Hubbell Receptacles.
- Multiple Bracket Options to Suit Every Application.
- "Assemble-to-Order" Available for Customized Power Strips.

## Features/Benefits

- Wide variety of sizes available.
- NEMA and IEC configurations.
- Cords available with Hubbell TWIST-LOCK® plugs.

## **Specifications**

- Housing Material: cold-rolled steel. Finish: Powder-coated, black.
- AC Voltage: 120V or 250V.
- Current Rating: 15, 20, 30 or 60 Amp.
- Outlets: NEMA 5-15R or 5-20R or IEC C-13 or C-19.
- Input Plug Cord: 10' cable with NEMA plug, IEC 320 C-20 inlet, or 60A IEC 309 plug.
- Surge Protection: Protection Modes: L-N, L-G, N-G. Joule Rating: 720.

## **Power Strips, Vertical Mount**

Can be mounted in all HPW cabinets and racks to distribute power to active equipment. All units include circuit breakers and full length mounting bracket. All units feature 10' cable (except PR20820I).

| Delivery: 1 strip, 1 ki | t mounting hardwa | ire, universo | al mounting bracket | s.       |           |        |         |             |
|-------------------------|-------------------|---------------|---------------------|----------|-----------|--------|---------|-------------|
| Electrical              | Receptacle        | Outlets       | Plug                | No. of   | Surge     |        | Current |             |
| Specification           | Туре              | Front         | Туре                | Circuits | Protected | Switch | Monitor | Catalog No. |
| 15A-120V                | NEMA 5-15R        | 10            | NEMA 5-15P          | 1        | No        | No     | No      | PR104       |
| 20A-120V                | NEMA 5-20R        | 10            | NEMA 5-20P          | 1        | No        | No     | No      | PR10420     |
| 15A-120V                | NEMA 5-15R        | 20            | NEMA 5-15P          | 1        | No        | No     | No      | PR206       |
| 20A-120V                | NEMA 5-20R        | 20            | NEMA 5-20P          | 1        | No        | No     | No      | PR20620     |
| 20A-120V                | NEMA 5-20R        | 20            | NEMA 5-20P          | 1        | No        | Yes    | Yes     | PR20820DRTL |
| 30A-120V                | NEMA 5-20R        | 20            | NEMA L5-30P         | 1        | No        | No     | No      | PR20830     |
| 20/16A /circuit<br>120V | NEMA 5-20R        | 20            | NEMA 5-20P          | 2        | No        | No     | No      | PR20820A*   |
| 20/16A-120/250V         | IEC 320C-13       | 20            | IEC 320 C20         | 1        | No        | No     | No      | PR20820I**  |
| 30/24A-250V             | IEC 320C-13       | 24            | NEMA L6-30P         | 1        | No        | No     | No      | PR24        |
|                         |                   |               |                     |          |           |        |         |             |

- \* PR20820A features (2) 20A circuits each fed by 10ft. cable w/ NEMA 5-20 plug.
- \*\* PR20820I includes an IEC 320 (C-20) inlet for power input.

| Mounting Brackets for Vertical Po | Mounting Br | ackets for | Vertical | Power Strips |
|-----------------------------------|-------------|------------|----------|--------------|
|-----------------------------------|-------------|------------|----------|--------------|

| Description   | Catalog No. |
|---|-------------|
| 'L' brackets - turned 'in', these are ideal for rack/rail mounting. Turned 'out' they extend your mounting options<br>an additional 8 inches. | PRSLB4      |
| Provides left, right, front or back rail mounting. May be installed in conjunction with other equipment mounted in the same 'U' space.        | PREZB       |



**H34**