

FLX Series Rack PDUs



FLX Series PDUs are part of Leviton's Make To Order (MTO) program. Build your custom PDU using the configurators listed on the previous page or online at www.leviton.com/configurator.

INPUT PLUG TYPES

NEMA 5-20P 120V	NEMA L5-20P 120V	NEMA L5-30P 120V	NEMA L6-20P 208V	NEMA L6-30P 208V
NEMA L21-20P 120/208V WYE	NEMA L21-30P 120/208V WYE	NEMA L15-20P 208V Delta	NEMA L15-30P 208V Delta	NEMA CS8365C 208V Delta

OUTPUT RECEPTACLE TYPES

NEMA 5-20R 120V	NEMA L6-20R 208V	IEC C13 208V	IEC C19 208V
------------------------	-------------------------	---------------------	---------------------





COMMON CONFIGURATIONS

Part numbers for several common configurations are listed here; simply select desired cord length and call your Leviton distributor to order. Use the Model Number Configurators on page 4-5 to find other versions to fit your needs.

Standard dimensions are 70"H x 2.3"W x 2"D. Units with UL489-rated circuit breakers, add an additional 1" of depth at the base of the PDU for the circuit breaker enclosure.

xx = Cord Length: Choose from 03-15 feet.

STANDARDS & CERTIFICATIONS
UL 60950-1 LISTED | #E228302

120V FLX SERIES							
PART NO.		INPUT				OUTPUT	
Basic (Unmetered)	Metered	Amperage	Cord Length	Plug Type	Overload Protection	Voltage	Receptacle Qty & Type
FB103-xxL	[A] FM103-xxL	20A	3'-15'	L5-20P	Yes	120V	(24) 5-20R
FB105-xxL	FM105-xxL	30A	3'-15'	L5-30P	Yes	120V	(24) 5-20R

208V FLX SERIES							
PART NO.		INPUT				OUTPUT	
Basic (Unmetered)	Metered	Amperage	Cord Length	Plug Type	Overload Protection	Voltage	Receptacle Qty & Type
FB201-xxL	FM201-xxL	20A	3'-15'	L6-20P	Yes	208V	(24) C13
FB203-xxL	FM203-xxL	30A	3'-15'	L6-30P	Yes	208V	(24) C13
FB204-xxL	FM204-xxL	20A	3'-15'	L6-20P	Yes	208V	(24) C13; (6) C19
FB206-xxL	[B] FM206-xxL	30A	3'-15'	L6-30P	Yes	208V	(24) C13; (6) C19
FB207-xxL	FM207-xxL	20A	3'-15'	L6-20P	Yes	208V	(12) L6-20R
FB212-xxL	FM212-xxL	30A	3'-15'	L6-30P	Yes	208V	(12) C19

208V 3-PHASE FLX SERIES							
PART NO.		INPUT				OUTPUT	
Basic (Unmetered)	Metered	Amperage	Cord Length	Plug Type	Overload Protection	Voltage	Receptacle Qty & Type
FB301-xxL	FM301-xxL	20A	3'-15'	L21-20P	Yes	120V	(24) 5-20R
FB307-xxL	FM307-xxL	20A	3'-15'	L21-20P	Yes	120V	(42) 5-20R
FB309-xxL	FM309-xxL	30A	3'-15'	L21-30P	Yes	120V	(42) 5-20R
FB313-xxL	FM313-xxL	20A	3'-15'	L21-20P	Yes	208V	(24) C13; (6) C19
FB315-xxL	[C] FM315-xxL	30A	3'-15'	L21-30P	Yes	208V	(24) C13; (6) C19
FB321-xxL	FM321-xxL	30A	3'-15'	L21-30P	Yes	120V/208V	(24) 5-20R; (6) L6-20R
FB324-xxL	FM324-xxL	30A	3'-15'	L21-30P	Yes	208V	(36) C13
FB325-xxL	FM325-xxL	20A	3'-15'	L21-20P	Yes	208V	(42) C13
FB327-xxL	FM327-xxL	30A	3'-15'	L21-30P	Yes	208V	(42) C13
FB333-xxL	FM333-xxL	30A	3'-15'	L21-30P	Yes	208V	(12) C19
FB337-xxL	FM337-xxL	50A	3'-15'	CS8365-C	Yes	208V	(24) C13; (6) C19
FB338-xxL	FM338-xxL	50A	3'-15'	CS8365-C	Yes	208V	(12) C19
FB339-xxL	FM339-xxL	30A	3'-15'	L21-30P	Yes	120V/208V	(20) C13; (4) C19; (2) 5-20R
FB403-xxL	FM403-xxL	30A	3'-15'	L15-30P	Yes	208V	(24) C13; (6) C19

Sold by:

