VOICE REINFORCEMENT

Voice Reinforcement **System ORATOR**

The Bogen Orator is a dual-channel, infrared (IR) wireless microphone/transmitter and mixeramplifier system that is designed to enhance a presenter's voice in all areas of the room. IR technology eliminates the interference and cross-talk from adjacent rooms that occurs with FM-based wireless products.



- **Orator System consists of:**
- 1 Receiver/Base Unit (ORB35) Security Cover Locking Keys
- 1 MIC/Transmitter (OMX1)
- Rechargeable Lithium Battery
- 1 Infrared Sensor (ORS1)
- Adjustable Microphone Lanyard

2 Pre-packaged System Options Available:



ORB35 Orator Base Unit Features:

- 7-Input mixer/amplifier/receiver with 4 AUX inputs, 1 priority paging (25V/70V/line), and 2 MIC/Transmitter inputs
- Dual front-mounted charging dock for MIC/Transmitter
- Amplifier output power: 35W
- Master Volume, plus separate volume controls for each input
- · 8-band EQ front-mounted bass and treble controls, plus 6-band rear-mounted graphic EQ
- Speaker impedances: 70V, 25V or 8-ohms
- · Output feeds: booster amp, subwoofer
- · Front-mounted AUX input
- · Front-mounted system output (for assistive listening devices, recording, etc.)
- · Page input with VOX-triggered priority override function
- Rotating, lockable front cover for tamper protection and secure storage of MIC/Transmitters and accessories
- Listed to UL Standard 60065 for US and Canada

OMX1 MIC/Transmitter Features:

- · Can be used as a handheld microphone as well as worn on a lanyard around the neck or as a body-pack with a user-supplied external microphone
- Built-in microphone with volume control
- Adjustable lanyard with break-away clasp for neck-worn applications
- Rugged, reliable, spring-wire belt clip
- Use built-in microphone or external microphone depending
- AUX input for wireless connection of audio sources (computers, MP3 players, etc.)
- Rechargeable, high-capacity Li-ion battery included
- · Comprehensive battery/status indicator


ORS1 IR Sensor Features:


- · Remotely mounted sensor connects via standard coaxial cable
- Add multiple sensors to improve reception in trouble spots



DISTRIBUTE SOUND EVENLY THROUGHOUT A ROOM

Typical room in which listeners sitting in the rear of the room hear only 25% of what the presenter says.





With Bogen ORATOR, individuals sitting at the back of the room can hear just as well as those who are sitting up front.

Easy Mount Wall Bracket

Specifically designed for easy 1-person mounting, special support stops help to locate receiver unit while installing hardware. The removal of 2 screws allows the ORB35 unit to rotate downward into a service position, allowing for easy access to rear controls and connections.

